

Elecraft P3 with SVGA-Option - Macros for Numeric-Keyboard

Num Lock ---	(/)	(*)	(Back Space) ---
---	SQ on	SQ off	---
(7)	(8)	(9)	(-)
M1-RPT	5up	Split 5up	free
(4)	(5)	(6)	(+)
M4	1up	Split 1up	free
(1)	(2)	(3)	(enter)
(0 / 00)		(.)	---
clean up		Mute	---

MEM	Key	Marco	Command Line
13	0	clean up	ft0;rt0;xt0;ln0;sq000;sq\$000;lk0;lk\$0;ag200;ag\$200;dv0;sb0;ra00;ra\$00;pa0;pa\$0;rx;
1	1	Memory 1	swt21;
2	2	Memory 2	swt31;
3	3	Memory 3	swt35;
4	4	Memory 4	swt39;
5	5	1kHz up	up4;
6	6	Split 1kHz up	swt13;swt13;upb4;ft1;dv0;rt0;xt0;lk1;
7	7	Memory 1 Repeat	swh21;
8	8	5kHz up	up7;
9	9	Split 5kHz up	swt13;swt13;upb7;ft1;dv0;rt0;xt0;lk1;
10	,	Mute	ag000;ag\$000;
11	/	Squelch on	sq005;
12	*	Squelch off	sq000;
	-	<i>free</i>	
	+	<i>free</i>	
---	(Enter)	<i>not able</i>	
---	Num	<i>not able</i>	
---	Back Space	<i>not able</i>	